Communications & Power Industries Tetrode





The 4CX7500A is a compact tetrode designed to be used in VHF power amplifer service. It features a type of internal structure which results in high RF operating efficiency up to 220 MHz. A dense mesh filament is used which contributes to the high performance capability of the tube. This tube is also recommended for use as a VHF TV linear amplifier.

FEATURES:

Maximum plate dissipation: 7,500 Watts
Maximum screen dissipation: 165 Watts
Maximum grid dissipation: 50 Watts
Frequency for max rating (CW): 220 MHz
Amplification factor: 8.0

Filament/cathode: Thoriated Tungsten

Voltage: 7.0 Volts
Current 110 Amps

Capacitance: Grounded cathode

Input: 145.0 pF
Output: 20.0 pF
Feedthrough: 0.53 pF

Capacitance: Grounded grid

Input: 74.1 pF
Output: 20.6 pF
Feedthrough: 0.7 pF
Cooling: Forced Air
Base: Special Coaxial

Air Socket: SK-340
Air Chimney: ---

Boiler: ---

Length: 9.27 in; 235.46 mm Diameter: 5.66 in; 143.76 mm

Weight: 8.4 lb; 3.8 kg

BENEFITS:

- Worldwide brand name recognition
- Over 85 years technical expertise

APPLICATIONS:

Communications



		MAXIMUI	M RATINGS	TYPICAL OPERATION				
Class of Operation	Type of Service	Plate Voltage (Volts)	Plate Current (Amps)	Plate Voltage (Volts)	Screen Voltage (Volts)	Plate Current (Amps)	Drive Power (Watts)	Output Power (kiloWatts)
С	RF amplifier	7,500	3.0	6,500	750	2.40	130	12.1
AB1	AF linear amplifier	7,500	3.0	7,500	1,250	2.20		10.0

With a history of producing high quality products, we can help you with your tetrode.

Contact us at MPPMarketing@cpii.com or call us at +1 650-846-2800. The data should be used for basic information only. Formal, controlled specifications may be obtained from CPI for use in equipment design.



Microwave Power Products Division 811 Hansen Way Palo Alto, California USA 94304 tel +1 650-846-2800 fax +1 650-856-0705 email MPPMarketing@cpii.com web www.cpii.com/MPP For more detailed information, please refer to the corresponding CPI technical description if one has been published, or contact CPI. Specifications may change without notice as a result of additional data or product refinement. Please contact CPI before using this information for system design.