Communications & Power Industries Tetrode





The 4CX5000R/8170W incorporates rugged internal construction features including a sturdy mesh filament which allows it to meet demanding vibration and shock specifications. The 4CX5000R/ 8170W is useful up to 110 MHz and is recommended for use as a radio frequency linear amplifier, a Class AB audio amplifier, or a Class C power amplifier or plate-modulated amplifier.

FEATURES:

Maximum plate dissipation: 5,000 Watts
Maximum screen dissipation: 250 Watts
Maximum grid dissipation: 75 Watts
Frequency for max rating (CW): 100 MHz

Amplification factor: 4.5

Filament/cathode: Thoriated Tungsten

Voltage: 7.5 Volts
Current 75 Amps

Capacitance: Grounded cathode

Input: 115.0 pF
Output: 20.5 pF
Feedthrough: 0.7 pF

Capacitance: Grounded grid

Input: 53.0 pF
Output: 21.5 pF
Feedthrough: 0.1 pF
Cooling: Forced Air
Base: Special Coaxial

Air Socket: SK-300A
Air Chimney: SK-306

Boiler: ---

Length: 9.13 in; 232 mm
Diameter: 4.94 in; 125.00 mm
Weight: 9.5 lb; 4.31 kg

BENEFITS:

Worldwide brand name recognitionOver 85 years technical expertise

APPLICATIONS:

• Communications



		MAXIMUM RATINGS		TYPICAL OPERATION				
Class of Operation	Type of Service	Plate Voltage (Volts)	Plate Current (Amps)	Plate Voltage (Volts)	Screen Voltage (Volts)	Plate Current (Amps)	Drive Power (Watts)	Output Power (kiloWatts)
С	RF amplifier	7,500	3.0	6,500	750	2.3	100	10.0
С	RF amplifier	5,000	2.5	5,000	500	1.4		5.8
AB1	RF linear amplifier	7,500	4.0	7,500	1,250	1.9		10.0
AB1	AF amplifier or modulator (2 tubes)	7,500	4.0	7,000	1,250	3.7		17.5

With a history of producing high quality products, we can help you with your tetrode.

Contact us at MPPMarketing@cpii.com or call us at +1 650-846-2800. The data should be used for basic information only. Formal, controlled specifications may be obtained from CPI for use in equipment design.

web



Microwave Power Products Division

811 Hansen Way Palo Alto, California USA 94304 tel +1 650-846-2800 fax +1 650-856-0705 email MPPMarketing@cpii.com

www.cpii.com/MPP

For more detailed information, please refer to the corresponding CPI technical description if one has been published, or contact CPI. Specifications may change without notice as a result of additional data or product refinement. Please contact CPI before using this information for system design.