Communications & Power Industries Tetrode





The 4PR60C/8252W is intended for pulse modulator service in circuits employing inductive or resistive loads. This tube unilaterally replaces the 715C, the 5D21 and the 4PR60B/8252. The internal structure of the tube has been strengthened to minimize the effects of shock and vibration. The 4PR60C/8252W has a maximum plate dissipation rating of 60 watts. It is cooled by radiation and convection, and it delivers pulse output power in the region of 300 kW with less than one kW of pulse driving power.

FEATURES:

Maximum plate dissipation: 60 Watts
Maximum screen dissipation: 8 Watts
Maximum grid dissipation: 1 Watt
Frequency for max rating (CW): --- MHz
Amplification factor: ---

Filament/cathode: Oxide Coated
Voltage: 26.0 Volts
Current: 2.1 Amps

Capacitance: Grounded cathode

Input: 43.0 pF
Output: 8.5 pF
Feedthrough: 1.5 pF

Capacitance: Grounded grid

Input: --- pF
Output: --- pF
Feedthrough: --- pF

Cooling: Radiation & Forced Air

Base: 4-Pin Special

Air Socket: --Air Chimney: --Boiler: ---

Length: 6.00 in; 152.40 mm
Diameter: 3.06 in; 77.90 mm
Weight: 12 oz; 0.34 gm

BENEFITS:

- Worldwide brand name recognition
- Over 85 years technical expertise

APPLICATIONS:

• Science



		MAXIMUM RATINGS		TYPICAL OPERATION				
Class of Operation	Type of Service	Plate Voltage (Volts)	Plate Current (Amps)	Plate Voltage (Volts)	Screen Voltage (Volts)	Plate Current (Amps)	Drive Power (Watts)	Output Power (kiloWatts)
	Switch Tube or PUIse Modulator	20,000	18.0	20 000	1,250	18.0		337.0

With a history of producing high quality products, we can help you with your tetrode.

Contact us at MPPMarketing@cpii.com or call us at +1 650-846-2800. The data should be used for basic information only. Formal, controlled specifications may be obtained from CPI for use in equipment design.



Microwave Power Products Division

811 Hansen Way Palo Alto, California USA 94304

+1 650-846-2800 tel +1 650-856-0705 email MPPMarketing@cpii.com www.cpii.com/MPP web

For more detailed information, please refer to the corresponding CPI technical description if one has been published, or contact CPI. Specifications may change without notice as a result of additional data or product refinement. Please contact CPI before using this information for system design.