## **Communications & Power Industries Triode**



Frequency

The YU-114 is a planar triode intended for use as a high voltage series regulator or switch tube. The compact, low inductance package allows fast rise and fall times and very short pulse operation. In air the maximum plate voltage is 15 kilovolts, and in insulating oil it is 25 kilovolts. The plate is conduction cooled and rated at 400 watts when used with the proper heatsink. The YU-114 has solder tabs for making connection to the heater, cathode and grid terminals.

## FEATURES:

Maximum plate dissipation: 400 Watts

Maximum screen dissipation: ---

Maximum grid dissipation:

Frequency for max rating (CW):

Amplification factor:

Filament/cathode:

Voltage:

Current:

2 Watts

--- MHz

700

Oxide

6.3 Volts

2.25 Amps

Capacitance: Grounded cathode

Input: 18.0 pF
Output: 0.03 pF
Feedthrough: 5.5 pF

Capacitance: Grounded grid

Input: --- pF
Output: --- pF
Feedthrough: --- pF

Cooling: Conduction
Base: Solder Tabs

Air Socket: --Air Chimney: --Boiler: ---

 Length:
 2.825 in; 7.18 cm

 Diameter:
 1.33 in; 3.38 cm

 Weight:
 2 oz; 56 gm

## **BENEFITS:**

- Worldwide brand name recognition
- Over 85 years technical expertise

## **APPLICATIONS:**

Science



		MAXIMUM RATINGS		TYPICAL OPERATION				
Class of Operation	Type of Service	Plate Voltage (Volts)	Plate Current (Amps)	Plate Voltage (Volts)	Screen Voltage (Volts)	Plate Current (Amps)	Drive Power (Watts)	Output Power (kiloWatts)
	Pulse Modulator, in Air Pulse Modulator, in Insulating Oil	15,000 25,000	10 10					

With a history of producing high quality products, we can help you with your triode.

Contact us at MPPMarketing@cpii.com or call us at +1 650-846-2800. The data should be used for basic information only.

Formal, controlled specifications may be obtained from CPI for use in equipment design.



Microwave Power Products Division 811 Hansen Way Palo Alto, California USA 94304 tel +1 650-846-2800 fax +1 650-856-0705 email MPPMarketing@cpii.com web www.cpii.com/MPP For more detailed information, please refer to the corresponding CPI technical description if one has been published, or contact CPI. Specifications may change without notice as a result of additional data or product refinement. Please contact CPI before using this information for system design.

©2020 Communications & Power Industries LLC. Company proprietary: use and reproduction is strictly prohibited without written authorization from CPI.